

## GX-3-D Air & Gas Pump



### TECHNICAL DATA

- ✓ Flow (L/min): 8.0
- ✓ Pressure (bar): 1.8
- ✓ Vacuum (bar): - 0.7
- ✓ Voltage (VDC): 12/24
- ✓ Current (Amp): 0.55/0.32
- ✓ Motor Code Key\*: 5
- ✓ Weight (g): 225
- ✓ Dimensions (mm): 80x78x31

### WIRING INSTRUCTIONS FOR BRUSHLESS MOTOR (3 Wires):

RED: +ve

BLACK: -ve

BLUE: PWM (Pulse Width Modulation) 0-5 V analog

\* Red and Blue wires may be joined together if PWM function is not needed.

### WIRING INSTRUCTIONS FOR BRUSHLESS MOTOR (4 Wires):

RED: +ve

BLACK: -ve

BLUE: PWM (Pulse Width Modulation) 0-5 V analog

GREEN: Motor Speed Feedback

\* Red and Blue wires may be joined together if PWM function is not needed.

# GX-3-D Air & Gas Pump (continued)

