



GX-3-S Air & Gas Pump





TECHNICAL DATA

Flow (L/min): 5.0
Pressure (bar): 1.8
Vacuum (bar): − 0.7
Voltage (VDC): 12/24
Current (Amp): 0.55/0.32
Motor Code Key*: 5

⊘ Weight (g): 155

Dimensions (mm): 70x55x31

WIRING INSTRUCTIONS FOR BRUSHLESS MOTOR (3 Wires):

RED: +ve

BLACK: -ve

BLUE: PWM (Pulse Width Modulation) 0-5 V analog

* Red and Blue wires may be joined together if PWM function is not needed.

WIRING INSTRUCTIONS FOR BRUSHLESS MOTOR (4 Wires):

RED: +ve

BLACK: -ve

BLUE: PWM (Pulse Width Modulation) 0-5 V analog

GREEN: Motor Speed Feedback

* Red and Blue wires may be joined together if PWM function is not needed.

Phone: 951-296-3397



GX-3-S Air & Gas Pump (continued)



